

Screw-mountable hoods / Hoods with bajonet lock



Specifications

Regulations: DIN VDE 0627, DIN VDE 0110,

DIN EN 61 984

Approvals: UR, CSA, SEV, MEIE, EZÚ, GOST

in preparation

Number of poles: 6 - 108 + PE

Electrical data:

See individual series.

Housings (grey, standard):

Material: Die-cast aluminium Surface: Powder-coated Fixing screws: Zinc-plated steel

Housing gasket: NBR

Temperature range: - 40 °C up to + 125 °C

Protection degree acc. to

DIN EN 60 529 when screwed: IP 68

Housings (silver, electromagnetic compatibility (EMC)):

Material: Die-cast aluminium
Surface: Electrically conducting

Coating is absolutely free of chrome and heavy metal

Fixing screws: Stainless steel
Housing gasket: NBR conducting
Temperature range: - 40 °C up to + 125 °C

Protection degree acc. to

DIN EN 60 529 when screwed: IP 68

Housings (black, for harsh environmental requirements):

Material: Die-cast aluminium
Surface: Powder-coated
Fixing screws: Stainless steel

Housing gasket: Viton

Temperature range: - 40 °C up to + 200 °C

Protection degree acc. to

DIN EN 60 529 when screwed: IP 68

Application hint

Heavy duty connectors are electrical devices which under proper use - under load - should not be inserted or separated.

Bajonet lock (Quick-lock).



The material is the same for all three housing versions.

Page

Screw-mountable hoods and hoods with bajonet lock

B 6, BB 10, BHT 6, DD 24, MOB 6 141



Screw-mountable hoods and hoods with bajonet lock

B 10, BB 18, BHT 10, DD 42, MOB 10 143



Screw-mountable hoods and hoods with bajonet lock

B 16, BB 32, BHT 16, BA 6, D 40, DD 72, MOB 16 145



Screw-mountable hoods and hoods with bajonet lock

B 24, BB 46, BHT 24, D 64, DD 108, MOB 24 147



Flange sets

140, 142, 144, 146

Protective caps

140, 142, 144, 146





Short overview of matching inserts for screw-mountable hoods of series B 6, BB 10, BHT 6, DD 24 and MOB 6

The housings on the following pages can be equipped with the inserts listed below:

	Screw term	inal inserts	Crimp conta	act carriers	Insulation displacement	ıt	Wirin for pa	ng adapters nel housings
B 6	Female insert, screw terminal insert, with wire protection part no. 710 106	Male insert, screw terminal insert, with wire protection part no. 710 206	Crimp contact carrier for female contacts part no. 710 306	Crimp contact carrier for male contacts part no. 710 406	Female insert, Male insert, insulation displacement, part no. 710 106 01 part no. 710 206	ement, fema 01 earth	ng adapter, ale insert, n pin right: no. 710 657	Wiring adapter, male insert, earth pin right: part no. 710 665
≽ p. 22	w/o wire protection part no. 710 769	w/o wire protection part no. 710 773	1	The state of the s	NEW		n pin left: no. 710 661	earth pin left: part no. 710 669
BB 10			Crimp contact carrier for female contacts part no. 710 311	Crimp contact carrier for male contacts part no. 710 411				
> p. 23			NE NE	W N				
BHT 6	Female insert, screw terminal, with wire protection, part no. 710 106 HT	Male insert, screw terminal, with wire protection, part no. 710 206 HT						
> p. 150	100							
DD 24			Crimp contact carrier for female contacts part no. 750 124	Crimp contact carrier for male contacts part no. 750 224				
> p. 56			1	Company of the Compan				
MOB 6	Female frame MO B6 fo	r 2 contact carriers	12		Male frame MO B6 for 2 contact carriers			OH III
≽ p. 69	for male and female co (coding A-B) for male and female cor	·	o. 770 006 o. 770 406	10	for male and female contacts (coding A-B) for male and female contacts (2 x PE)	part no.		12 1

> The page reference at the left of the table guides you to the detailed overview of inserts

Contacts for crimp contact carriers of series ...

B 6: page 22 DD 24: page 56

MO: page 71, 73, 75, 77, 79, 81 and 83

Description	Part No.	Accessories for hoods (screw-mountable/with bajonet lock)		EAN-No. 4015609
Flange sets for screw-mountable hoods with 2 flanges, 4 screws, 4 fan-typ lock washer Female or male insert is mounted directly on the flanges - saves the panel housing!	s. 717 000 FS	6668	1 25	419678
for hoods with bajonet lock with 2 flanges, 4 screws, 4 fan-typ lock washer Female or male insert is mounted directly on the flanges -saves the panel housing!	s. 727 000 FS	0000	1 25	470198



	1		1		
Description	Part no.	М	Hoods (screw-mountable / with bajonet lock) for series B 6, BB 10, BHT 6, DD 24, MOB 6		EAN-No. 4015609
Screw-mountable ho	ood		2ea, M6x18 with		
Height 100 mm, top cable entry			steel thrust washer and O-Ring	10	
grey 1) silver 2) black 3)	717 106 OV 717 106 OVEM 717 106 OVSP	1 x M 20 1 x M 20 1 x M 20	92 57	284 284 284	415335 415342 415373
Height 100 mm, top cable entry			137 Sealing	10	
grey 1) silver 2) black 3)	717 206 OV 717 206 OVEM 717 206 OVSP	1 x M 25 1 x M 25 1 x M 25		278 278 278	415403 415397 415427
Hood with bajonet lo	ock				
Height 100 mm, top cable entry				10	
grey 1) silver 2) black 3)	727 106 OV 727 106 OVEM 727 106 OVSP	1 x M 20 1 x M 20 1 x M 20	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or 70 777 000 FS (boods with beingant lock)	299 299 299	469192 469208 469215
Height 100 mm, top cable entry			52 For bajonet lock For screw lock	10	
grey 1) silver 2) black 3)	727 206 OV 727 206 OVEM 727 206 OVSP	1 x M 25 1 x M 25 1 x M 25	(22/000FS) (7/17000FS)	293 293 293	469222 469246 469253
Screw-mountable ho	ood		2 ea. M6x18 with steel thrust washer and O-Ring 2 ea. bajonet locks		
Height 100 mm, side cable entry				10	
grey 1) silver 2) black 3)	717 506 OV 717 506 OVEM 717 506 OVSP	1 x M 20 1 x M 20 1 x M 20	92 57	284 284 284	415434 415441 415458
Height 100 mm, side cable entry		read M 32 or 40 on request	- Sealing	10	
grey ¹⁾ silver ²⁾ black ³⁾	717 606 OV 717 606 OVEM 717 606 OVSP	1 x M 25 1 x M 25 1 x M 25		278 278 278	415472 415489 415496
Hood with bajonet lo	ock		Carrier Annual Control		
Height 100 mm, side cable entry				10	
grey 1) silver 2) black 3)	727 506 OV 727 506 OVEM 727 506 OVSP	1 x M 20 1 x M 20 1 x M 20	Panel cut out: Flange mounting: 1 x flange set has to ordered separately: 717 000 FS (screw-mountable hoods) or 70 727 000 FS (bods with beingen lock)	299 299 299	469260 469277 469284
Height 100 mm, side cable entry		read M 32 or 40 on request	52 For bajonet lock For screw lock	10	
grey ¹⁾ silver ²⁾ black ³⁾	727 606 OV 727 606 OVEM 727 606 OVSP	1 x M 25 1 x M 25 1 x M 25	(727000FS) (717000FS)	293 293 293	469291 469307 469314
Protective caps				40	
for screw-mountable hoods for mounting side and hood, for snapping on, with retaining co		717 698		10 26	424702
for mounting side, with screw lo with retaining cord, IP 65	ck,	717 702	المراجعة الم	41	424863
for hoods with bajonet lock for mounting side and hood, for snapping on, with retaining or	ord IP 50	727 620		10 26	469789
for mounting side, with bajonet keep with retaining cord, IP 65		727 624		56	469840

2) silver = EMC (electromagnetic compatibility)



Short overview of matching inserts for screw-mountable hoods of series B 10, BB 18, BHT 10, DD 42 and MOB 10

The housings on the following pages can be equipped with the inserts listed below:

	Screw term	inal inserts	Crimp cont	act carriers	Insulation displacemen inserts	t Wiri for pa	ng adapters anel housings
B 10	Female insert, screw terminal, with wire protection, part no. 710 110	Male insert, screw terminal, with wire protection, part no. 710 210	Crimp contact carrier for female contacts part no. 710 310	Crimp contact carrier for male contacts part no. 710 410	Female insert, insulation displacement, insulation displacement, part no. 710 110 01 part no. 710 210 0		Wiring adapter, male insert, earth pin right: part no. 710 666
> page 24 - 25	1	-	Salta	PEREN N	NEW		
24 - 23	without wire protection part no. 710 770	without wire protection part no. 710 774	TREET,		Sanaa S	earth pin left: part no. 710 662	earth pin left: part no. 710 670
BB 18			Crimp contact carrier for female contacts part no. 710 318	Crimp contact carrier for male contacts part no. 710 418			
> p. 25			NE NE	W			
BHT 10	Female insert, screw terminal, with wire protection, part no. 710 110 HT	Male insert, screw terminal, with wire protection, part no. 710 210 HT					
≽ p. 152		THE PARTY OF					
DD 42			Crimp contact carrier for female contacts part no. 750 142	Crimp contact carrier for male contacts part no. 750 242			
≽ p. 57				Tunn P			
MOB 10	Female frame MO B10 for male and female cor (coding A-C)		o. 770 010	6	Male frame MO B10 for 3 contact carriers for male and female contacts (coding A-C)	part no. 770 110	CALL S
> p. 69	for male and female con	tacts (2 x PE) part n	o. 770 410	22.5	for male and female contacts (2 x PE)	part no. 770 510	22190

> The page reference at the left of the table guides you to the detailed overview of inserts

Contacts for crimp contact carriers of series ...

B 10: page 24 DD 42: page 57

MO: page 71, 73, 75, 77, 79, 81 and 83

Description	Part No.	Accessories for hoods (screw-mountable/with bajonet lock)		EAN-No. 4015609
Flange sets for screw-mountable hoods		6668	1	
with 2 flanges, 4 screws, 4 fan-typ lock washer. Female or male insert is mounted directly on the flanges - saves the panel housing! for hoods with bajonet lock	s. 717 000 FS	0000	25	419678
with 2 flanges, 4 screws, 4 fan-typ lock washer. Female or male insert is mounted directly on the flanges - saves the panel housing!	s. 727 000 FS	0000	1 25	470198



			Hoods (screw-mountable / with bajonet lock) for series		
Description	Part No.	M	B 10, BB 18, BHT 10, DD 42, MOB 10	g	EAN-No. 4015609
Screw-mountable ho	oods		2 ea. M6x18 with		
Height 100 mm, top cable entry grey 1) silver 2) black 3)	717 110 OV 717 110 OVEM 717 110 OVSP	1 x M 20 1 x M 20 1 x M 20	steel thrust washer and O-Ring bajonet locks	10 318 318 318	382972 382989 382996
Height 100 mm, top cable entry grey 1) silver 2) black 3)		1 x M 25 1 x M 25 1 x M 25 1 x M 25	150 57 Sealing	10 310 310 310	383009 383016 383023
Hoods with bajonet l	lock				
Height 100 mm, top cable entry grey ¹⁾ silver ²⁾ black ³⁾	727 110 OV 727 110 OVEM 727 110 OVSP	1 x M 20	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or 727 000 FS (hoods with bajonet lock)	10 333 333 333	469321 469338 469345
Height 100 mm, top cable entry grey 1) silver 2) black 3)		1 x M 25 1 x M 25 1 x M 25 1 x M 25	For bajonet lock (727000FS)	10 325 325 325	469352 469369 469376
Screw-mountable ho	ood		2 ea. M6x18 with steel thrust washer and 0-Ring 2 ea.		
Height 100 mm, side cable entry grey 1) silver 2) black 3)	717 510 OV 717 510 OVEM 717 510 OVSP	1 x M 20 1 x M 20 1 x M 20	105	10 318 318 318	345595 383153 383160
Height 100 mm, side cable entry grey 1) silver 2) black 3)		1 x M 25 1 x M 25 1 x M 25 1 x M 25 1 x M 25	Sealing	10 310 310 310	311439 383177 383184
Hood with bajonet lo	ock				
Height 100 mm, side cable entry				10	
grey 1) silver 2) black 3)	727 510 OV 727 510 OVEM 727 510 OVSP	1 x M 20	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or 727 000 FS (hoods with bajonet lock)	333 333 333	469383 469390 469406
Height 100 mm, side cable entry grey 1) silver 2) black 3)			For bajonet lock (717000FS) For screw lock (717000FS)	10 325 325 325	469413 469420 469437
Protective caps					
for screw-mountable hoods for mounting side and hood, for snapping on, with retaining co	ord, IP 50	717 699		1 29	424719
for mounting side, with screw loowith retaining cord, IP 65	ck,	717703		44	424870
for hoods with bajonet lock for mounting side and hood, for snapping on, with retaining co	ord, IP 50	727 621		10 29	469796
for mounting side, with bajonet lowith retaining cord, IP 65		727 625		59	469857



Short overview of matching inserts for screw-mountable hoods of series B 16, BB 32, BHT 16, BA 6, D 40, DD 72 and MOB 16

The housings on the following pages can be equipped with the inserts listed below:

	Screw term	ninal inserts	Crimp conta	act carriers		lisplacement erts	Wiring for pan	g adapters iel housings
B 16	Female insert, screw terminal, part no. 710 116	Male insert, screw terminal, part no. 710 216	Crimp contac carrier for female contacts, part no. 710 316	Crimp contact carrier for male contacts, part no. 710 416	Female insert, insulation displacement, part no. 710 116 01	Male insert, insulation displacement, part no. 710 216 01	Wiring adapters, female insert, earth pin right: part no. 710 659	Wiring adapters, male insert, earth pin right: part no. 710 667
page 26 - 27	Samuel Comments	THE PERSON NAMED IN	1	SHEETE !	The state of	EW	earth pin left: part no. 710 663	earth pin left: part no. 710 671
B 32			Crimp contact carrier for female contacts part no. 710 333	Crimp contact carrier for male contacts part no. 710 433				
p. 27			NE NE	W				
3HT 16	Female insert, screw terminal, part no. 710 116 HT	Male insert, screw terminal, part no. 710 216 HT						
p. 154	Samuel .	A STREET						
BA 6	Female insert, screw terminal, part no. 710 620	Male insert, screw terminal, part no. 710 621						
p. 34		15000						
40			Crimp contact carrier for female contacts, part no. 720 340	Crimp contact carrier for male contacts, part no. 720 440			Wiring adapter, female insert, earth pin left: part no. 720 633	Wiring adapter male insert, earth pin left: part no. 720 63
page 44 - 45			1				3	1
DD 72			Crimp contact carrier, for female contacts, part no. 750 172	Crimp contact carrier, for male contacts, part no. 750 272				
page 58 - 59			4	Panadan T				
//OB 16 p. 69	Female frame MO B16 for male and female co (coding A - E)		art no. 770 016	1	Male frame MO B16 for for male and female co (coding A - E		art no. 770 116	and the

> The page reference at the left of the table guides you to the detailed overview of inserts

Contacts for crimp contact carriers of series B 16: p. 26 / D 40: p. 45 / DD 72: p. 59 / MO: p. 71, 73, 75, 77, 79, 81 and 83

Description	Part No.	Accessories for hoods (screw-mountable/with bajonet lock)		EAN-No. 4015609
Flange sets for screw-mountable hoods with 2 flanges, 4 screws, 4 fan-typ lock washer Female or male insert is mounted directly on the flanges - saves the panel housing!	s. 717 000 FS	6666	1 25	419678
for hoods with bajonet lock with 2 flanges, 4 screws, 4 fan-typ lock washer Female or male insert is mounted directly on the flanges -saves the panel housing!	s. 727 000 FS	9999	1 25	470198



Description	Part No.	М	Hoods (screw-mountable / with bajonet lock) for series B 16, BB 32, BHT 16, BA 6, D 40, DD 72, MOB 16		EAN-No. 4015609
Screw-mountable ho	oods		2 ea. M6x18 with C steel thrust washer and O-Ring		
Height 100 mm, top cable entry			2 ea. bajonet locks	40	
grey 1) silver 2) black 3)	717 216 OV 717 216 OVEM 717 216 OVSP	1 x M 25 1 x M 25 1 x M 25	126	10 344 344 344	383030 383047 383054
Height 100 mm, top cable entry grey 1) silver 2) black 3)	717 316 OV 717 316 OVEM 717 316 OVSP	Thread M 40 on request 1 x M 32 1 x M 32 1 x M 32		10 336 336 336	383061 383078 309412
Hoods with bajonet	lock		1		
Height 100 mm, top cable entry				10	
grey 1) silver 2) black 3)	727 216 OV 727 216 OVEM 727 216 OVSP	1 x M 25 1 x M 25 1 x M 25	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or	359 359 359	469444 469451 469468
Height 100 mm, top cable entry		Thread M 40 on request	727 000 FS (hoods with bajonet lock) 103 For bajonet lock For screw lock	10	
grey 1) silver 2) black 3)	727 316 OV 727 316 OVEM 727 316 OVSP	1 x M 32 1 x M 32 1 x M 32	(727000FS) (717000FS)	351 351 351	469475 469499 469505
Screw-mountable ho	oods		2 ea. M6x18 with steel thrust washer and O-Ring and O-R		
Height 100 mm, side cable entry				10	
grey 1) silver 2) black 3)	717 616 OV 717 616 OVEM 717 616 OVSP	1 x M 25 1 x M 25 1 x M 25	126 57 171 Sealing	344 344 344	345601 383191 309429
Height 100 mm, side cable entry		Thread M 40 on request	Searing	10	
grey 1) silver 2) black 3)	717 716 OV 717 716 OVEM 717 716 OVSP	1 x M 32 1 x M 32 1 x M 32		336 336 336	383207 383214 383221
Hoods with bajonet	lock				
Height 100 mm, side cable entry				10	
grey 1) silver 2) black 3)	727 616 OV 727 616 OVEM 727 616 OVSP	1 x M 25 1 x M 25 1 x M 25	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or	359 359 359	469529 469536 469550
Height 100 mm, side cable entry		Thread M 40 on request	103 727 000 FS (hoods with bajonet lock) 86 For bajonet lock For screw lock	10	
grey 1) silver 2) black 3)	727 716 OV 727 716 OVEM 727 716 OVSP	1 x M 32 1 x M 32 1 x M 32	(727000FS)	351 351 351	469581 469598 469604
Protective caps					
for screw-mountable hoods for mounting side and hood, for snapping on, with retaining co		717 700		10 33	424825
for mounting side, with screw lo with retaining cord, IP 65	ck,	717 704		49	424887
for hoods with bajonet lock for mounting side and hood, for snapping on, with retaining or	ord IP 50	727 622		10 33	469826
for mounting side, with bajonet lowith retaining cord, IP 65		727 626		64	469864



Short overview of matching inserts for screw-mountable hoods of series B 24, BB 46, BHT 24, D 64, DD 108 and MOB 24

The housings on the following pages can be equipped with the inserts listed below:

	Screw term	inal inserts	Crimp conta	act carriers	Insulation d	isplacement erts	Wiring for pane	adapters housings
B 24	Female insert, screw terminal, with wire protection part no. 710 124	Male insert, screw terminal, with wire protection part no. 710 224	Crimp contact carrier for female contacts part no. 710 324	Crimp contact carrier for male contacts part no. 710 424	Female insert, insulation displacement, part no. 710 124 01	Male insert, insulation displacement, part no. 710 224 01	Wiring adapter, female insert, earth pin right: part no. 710 660	Wiring adapter, male insert, earth pin right: part no. 710 668
> page 28 - 29	The second	minima.	***************************************	deserveres "	the But	NEW		
	without wire protection ArtNr. 710 772	without wire protection part no. 710 776	- contract (earth pin left: part no. 710 664	earth pin left: part no. 710 672
BHT 24	Female insert, screw terminal, with wire protection, part no. 710 124 HT	Male insert, screw terminal, with wire protection, part no. 710 224 HT						
> p. 156	management)	minima						
BB 46			Crimp contact carrier for female contacts part no. 710 346	Crimp contact carrier for male contacts part no. 710 446				
≽ p. 29								
D 64			Crimp contact carrier for female contacts part no. 720 364	Crimp contact carrier for male contacts part no. 720 464			Wiring adapter, female insert, earth pin left: part no. 720 635	Wiring adapter, male insert, earth pin left: part no. 720 634
> page 47 - 48				#			1	
DD 108			Crimp contact carrier for female contacts part no. 750 108	Crimp contact carrier for male contacts part no. 750 208				
≽ page 60 - 61			3	The state of the s				
MOB 24	Female frame MO B24 for male and female cor		D. 770 024	4	Male frame MO B24 for for male and female cor		rt no. 770 124	-
> p. 69	(coding A-G) for male and female con		o. 770 424	ELEX BY	(coding A-G) for male and female con		rt no. 770 324	22223

> The page reference at the left of the table guides you to the detailed overview of inserts

 $\textbf{Contacts for crimp contact carriers of series} \quad \textbf{B 24:} \ p. \ 28 \ / \ \textbf{D 64:} \ p. \ 48 \ / \ \textbf{DD 108:} \ p. \ 61 \ / \ \textbf{MO:} \ p. \ 71, \ 73, \ 75, \ 77, \ 79, \ 81 \ and \ 83$

Description	Part No.	Accessories for hoods (screw-mountable/with bajonet lock)	9	EAN-No. 4015609
Flange sets		DIE (1		
for screw-mountable hoods with 2 flanges, 4 screws, 4 fan-typ lock washer. Female or male insert is mounted directly on the flanges - saves the panel housing!	s. 717 000 FS	0000	1 25	419678
for hoods with bajonet lock with 2 flanges, 4 screws, 4 fan-typ lock washer. Female or male insert is mounted directly on the flanges - saves the panel housing!	s. 727 000 FS	6666	1 25	470198



			Hoods (saraw mauntahla / with		
			Hoods (screw-mountable / with bajonet lock) for series B24, BB46,		TANIN-
Description	Part No.	М	BHT 24, D 64, DD 108, MOB 24	g	EAN-No. 4015609
Screw-mountable ho	oods		2 ea. M6x18 with 2 ea.		
Height 100 mm, top cable entry			steel thrust washer and O-Ring Section 1 Secti	10	
grey 1) silver 2)	717 324 OV 717 324 OVEM	1 x M 32 1 x M 32		433	383085 383108
black 3)	717 324 OVSP	1 x M 32	152 57	433 433	383115
Height 100 mm, top cable entry			→ 197	10	
grey 1) silver 2)	717 424 OV 717 424 OVEM	1 x M 40 1 x M 40		428 428	383122 383139
black 3)	717 424 OVSP	1 x M 40		428	383146
Hoods with bajonet	lock				
Height 100 mm, top cable entry				10	
grey 1) silver 2)	727 324 OV 727 324 OVEM	1 x M 32 1 x M 32		448 448	469611 469628
black 3)	727 324 OVSP	1 x M 32	Flange mounting: Panel cut out: 1 x flange set has to be ordered separately. 717 000 FS (screw-mountable hoods) or	448	469642
Height 100 mm, top cable entry			130 727 000 FS (Screw-incultable hoods) of 112 727 000 FS (hoods with bajonet lock) For bajonet lock	10	
grey 1) silver 2)	727 424 OV 727 424 OVEM	1 x M 40 1 x M 40	(727000FS) (717000FS)	443 443	469659 469666
black 3)	727 424 OVSP	1 x M 40		443	469673
Screw-mountable ho	oods		2 ea. M6x18 with steel thrust washer and O-Ring 2 ea. bajonet locks		
Height 100 mm, side cable entry			\$ 152 152 152 152 152 152 152 152 152 152	10	
grey 1) silver 2)	717 724 OV	1 x M 32	152	443	346518
black 3)	717 724 OVEM 717 724 OVSP	1 x M 32 1 x M 32	197 Sealing	443 443	383238 383245
Height 100 mm, side cable entry				10	
grey 1)	717 824 OV	1 x M 40		428	383252
silver ²⁾ black ³⁾	717 824 OVEM 717 824 OVSP	1 x M 40 1 x M 40		428 428	383269 383276
Hoods with bajonet	lock				
Height 100 mm, side cable entry				40	
grey 1)	727 724 OV	1 x M 32		10 448	469680
silver ²⁾ black ³⁾	727 724 OVEM 727 724 OVSP	1 x M 32 1 x M 32	Panel cut out: Flange mounting: 1 x flange set has to be ordered separately.	448 448	469697 469710
Hainbi 100 mana aida aabla amin.			717 000 FS (screw-mountable hoods) or 727 000 FS (hoods with bajonet lock)		
Height 100 mm, side cable entry grey 1)	727 824 OV	1 x M 40	112 For bajonet lock (727000FS) For screw lock (727000FS)	10 443	469741
silver ²⁾ black ³⁾	727 824 OVEM	1 x M 40		443	469765
Diack ⁹	727 824 OVSP	1 x M 40		443	469772
Protective caps					
for screw-mountable hoods for mounting side and hood,		717 701		10 39	424856
for snapping on, with retaining co for mounting side, with screw lo					
with retaining cord, IP 65		717 705		55	424900
for hoods with bajonet lock				10	
for mounting side and hood, for snapping on, with retaining co	ord, IP 50	727 623		39	469833
for mounting side, with bajonet lowith retaining cord, IP 65	ock,	727 627		70	469888
with retaining cord, if to					

²⁾ silver = EMC (electromagnetic compatibility)



Screw-mountable hoods -

this alternative saves the panel housing.



Up to now you have the following two possibilities if you want to create a professional heavy duty connection:

1. A panel housing + insert which forms one single unit with the hood + insert.
Protection degree: IP 65.

2. A panel housing without insert, so that prefabricated cables can be led through. This forms a single unit together with the wire-through housing (two halfshells, that surround the cable and act as a seal). Protection degree IP 54.



NEW: Two unexpensive panel flanges for the accomodation of the insert form a unit together with the screw-mountable hood + insert.

Protection degree IP 68. Matching with inserts of series B 6-/10-/16-/24-pole as well as with series BB, BHT, BA, D, DD, MOB.



Screw-mountable hoods

- Inside seal as protection against moisture. Raised protection degree IP 68.
- captive hexagon slot head screws M 6 (key width 10 mm, slot width 1,4 mm)

Three housing versions:

- 1. Standard version
- 2. for harsh environmental requirements
- 3. for EMC (electromagnetic compatibility)

Cable entries

Top or side cable entry. The housings have the following threads:

series B 6: M 20 or M 25

series B 10: M 20 or M 25

• series B 16: M 25 or M 32

series B 24: M 32 or M 40

On request you can get any drill hole with M 20 up to M 40 in any series.

In series B 6 top cable entry max. M 25.



Mounted panel flange

Switch cabinet cut-out


panel flange

Panel flange set

Consisting of two flanges, 4 self-cutting screws (M 4) and 4 fan-type lock washers.

On standard switch cabinet cut-outs the two flanges are fixed with metric screws M 4 or M 5 and matching nuts.

screw-mountable hood





Second new version with **bajonet lock:**

